Panasonic

Super Dynamic Full HD Dome Network Camera
WV-SFN631L

Super Dynamic HD Dome Network Camera
WV-SFN611L

i-PRO SmartHD **6** Series

Onvif S

WV-SFN631L   WV-SFN611L

SD | ENHANCED Super Dynamic | VIQS Variable Image Quality on Specified area | H.264 JPEG | FULL HD Full High Definition 1080/60p (WV-SFN631L) | HD High Definition 720/60p (WV-SFN611L) | day/night IR removable | IR LED | HLC (As of June 2014) | Fog sand Compensation | Auto Back Focus

Full HD / 1,920 x 1,080 60 fps H.264 Network Camera featuring *Super Dynamic* (WV-SFN631L)
HD / 1,280 x 720 60 fps H.264 Network Camera featuring *Super Dynamic* (WV-SFN611L)

Key Features

- **1080p** Full HD / **720p** HD images up to **60 fps**[*1]
- Approximate 1/3 inches, high sensitivity MOS Sensor
- Super high resolution at Full HD/1,920 x 1,080 created by high sensitivity MOS Sensor. (WV-SFN631L only)
- **Multiple H.264 (High profile) streams (max. 4 streams)** and JPEG streams ensure simultaneous real time monitoring and high resolution recording by new enhanced "UniPhier®", Panasonic's proprietary System LSI platform.
- Maximum Screen Size is 2,048 x 1,536* @30fps, H.264 (WV-SFN631L only)
  * Used by super resolution techniques
- *Enhanced Super Dynamic*[*1] and ABS (Adaptive Black Stretch) technologies deliver **133 dB** wider dynamic range compared to conventional cameras.
- **Multi process NR & 3D-DNR** ensures noise reduction in various conditions.
- High sensitivity with Day & Night (IR) function:
  WV-SFN631L: 0.04 lx (Color), 0.01 lx (B/W) at F1.3
  WV-SFN611L: 0.01 lx (Color), 0.003 lx (B/W) at F1.3
- **IR LED** equipped: The equipped infrared LED makes it possible to take pictures at zero lx.
- **IR LED** is controlled to match the environment, thereby the camera provides clear images of human faces without white blur.
- New camera attachment bracket allows an **easy camera installation** toward all four directions.
- **High Speed ABF (Auto Back Focus) and Motorized Zoom** ensures easy installation.
- Newly developed lens with aperture control function realizes the best focus in any environment.
- **VIQS** (Variable Image Quality on Specified area) technology allows the designated **eight areas** to retain higher image quality while the excluded area will have a decreased image quality, which enables to use lower image file size and bit rate.
- Cropping function enables to provide whole image and the part image simultaneously. Up to 4 image capture areas can be specified, and it is also possible to control the sequence.
- *Face Super Dynamic* technology ensures clear face image.
- Lens distortion compensation for the distorted images can be adjusted 256 steps.
- Electronic sensitivity enhancement: Auto (Up to 16/30s) / OFF
- Selectable light control modes:
  Outdoor scene,Indoor scene (50 Hz) / Indoor scene (60 Hz),Fix shutter Indoor scene (50 Hz/60Hz): Flicker caused by fluorescent lightning will be automatically compensated.
- 3x (WV-SFN631L), 2x (WV-SFN611L) extra optical zoom at 640 x 360 resolution
- 2x, 4x digital zoom controlled by browser
- VMD (Video Motion Detection) with 4 programmable detection areas, 15 steps sensitivity level and 10 steps detection size
- Privacy Zone can mask up to 8 private areas, such as house windows and entrances/exits.
- Camera title display: Up to 20 alphanumeric characters on the browser
- Alarm sources including 3 terminal input, VMD and Panasonic alarm command can trigger actions such as SDXC/SDHC/SD memory recording, FTP image transfer, E-mail notification, Indication on browser, Alarm terminal output, and Panasonic alarm protocol output.

- Full duplex bi-directional audio allows interactive communication between camera site and monitoring site.
- JPEG Image compression ratio can be changed by alarm so that higher quality image can be provided.
- Prioritized stream control: One of the video streams can be prioritized when multiple recorders or client PCs are accessing the camera so that the recorder or the client PC can maintain the frame rate.
- **Double SDXC/SDHC/SD Memory card slots** for manual recording (H.264 / JPEG), alarm recording (H.264 / JPEG) and backup upon network failure (H.264 / JPEG). Realize long-term recording and auto backup function.
- Newly developed dome cover provides clearer images above the horizontal. Thereby, it expands the tilting range of the lens.
- Face detection function detects the position of human face and the information is sent by XML or video stream.(Optional *As of June 2014)
- Can be added new intelligent extension software (Optional *As of June 2014) in addition to built-in VMD (Video Motion Detection), alarm function.
- **Fog compensation function** equipped as standard.
- **Super Chroma Compensation** function realizes a better color reproducibility even in low illumination.
- H.264 max. bit rate/client and Total bit rate control allows flexible network traffic management. Frame rate priority mode controls bit rate and compression ratio to provide the specified frame rate.
- Internet mode: H.264 images can be transmitted over HTTP protocol.
- Multi-language: English / Italian / French / German / Spanish / Portuguese / Russian / Chinese / Japanese
- IPv4/IPv6 protocol supported
- Supports SSL, DDNS (viewnetcam, RFC2136)
- Still images (JPEG) can be viewed on mobile phones via Internet.
- Onvif compliant model

*1 Super Dynamic function is automatically set off on 60fps mode

Optional Accessories

Ceiling Mount Bracket **WV-Q105A**

Ceiling Mount Bracket **WV-Q174B**

Smoke Dome Cover **WV-CF5SA**

Specifications

Camera	Image Sensor	Approx. 1/3 type MOS image sensor
	Effective Pixels	WV-SFN631L : Approx. 2.4 mega pixels, WV-SFN611L : Approx. 1.3 mega pixels
	Scanning Mode	Progressive scan
	Scanning Area	WV-SFN631L : 5.346 mm (H) x 3.336 mm (V) {7/32 inches(H) x 1/8 inches(V) } WV-SFN611L : 4.864 mm (H) x 3.891 mm (V) {3/16 inches(H) x 5/32 inches(V) }
	Minimum Illumination	WV-SFN631L : 　Color: less than 0.04 lx, BW: 0.01 lx (F1.3, Maximum shutter : Max. 1/30s, Gain : On(High)) 　Color: less than 0.003 lx, BW 0.0007 lx (F1.3, Maximum shutter : Max. 16/30s, Gain : On(High)) *1 WV-SFN611L : 　Color: less than 0.01 lx, BW: 0.003 lx (F1.3, Maximum shutter : Max. Off (1/30s), Gain : On(High)) 　Color: less than 0.0007 lx, BW 0.0002 lx (F1.3, Maximum shutter : Max. : Max. 16/30s, Gain:On(High)) *1
	IR LED Light	Off/Auto(High/Mid/Low)
	IR LED irradiation distance	Approx. 30 m {98.43 feet}
	White Balance	AWC (2,000 ~ 10,000 K), ATW1 (2,700 ~ 6,000 K), ATW2 (2,000 ~ 6,000 K)
	Light Control Mode	Outdoor scene : Automatic integration of ALC and ELC Indoor scene [50 Hz] : Automatic integration of ALC and ELC with flickerless Indoor scene [60 Hz] : Automatic integration of ALC and ELC with flickerless
	Shutter Speed	[2 mega pixel [16:9](60 fps mode)/ 1.3 mega pixel [16:9](60 fps mode)] OFF(1/30), 1/100, 1/120, 1/250, 1/500, 1/1000, 1/2000, 1/4000,1/10000 Other than [2 mega pixel [16:9](60 fps mode)/ 1.3 mega pixel [16:9](60 fps mode)] OFF(1/30), 3/100, 3/120, 2/100, 2/120, 1/100, 1/120, 1/250,1/500, 1/1000, 1/2000, 1/4000, 1/10000
	Super Dynamic*2	On(High) / On(Normal) / Off
	Face Super Dynamic	ON / OFF (Only at Super Dynamic : ON)
	Adaptive Black Stretch	ON / OFF (Only when Super Dynamic OFF)
	Fog compensation	ON / OFF (Only when Super Dynamic / Adaptive black stretch: Off)
	AGC	ON (LOW, MID, HIGH) / OFF
	Electronic Sensitivity UP	max. 1/1000 s, max. 1/500 s, max. 1/250 s, max. 1/100 s, max. 1/60 s, max. 1/30 s, max. 2/30 s, max. 4/30 s, max. 6/30 s, max. 10/30 s, max. 16/30 s
	Day & Night (IR)	Off/ On/ Auto1 (Normal)/ Auto2 (IR Light)/ Auto3 (SCC)
	Dynamic Range	133 dB typ. (Super Dynamic: ON, Light Control Mode : indoor)
	Digital Noise Reduction	High / Low
	Video Motion Detection	4 areas, Sensitivity : 15 steps, Detection size : 10 steps
	Privacy Zone	Up to 8 zones
	VIQS	Up to 8 zones
	Camera Title (OSD)	Up to 20 characters (alphanumeric characters, marks)
	Electric Zoom	TELE / WIDE , Auto Coarse adjustment of Focus
	Focus Adjustment	ABF / MANUAL(Html only)
	Lens Distortion Compensation	256 steps
Lens	Vari Focal Length	2.8 ~ 10mm {1/8 inches – 13/32 inches}
	Angular Field of View	WV-SFN631L [16 : 9 mode] Horizontal : 29.3° (TELE) - 104.1° (WIDE) 　　　　　　　　　　　　 Vertical : 16.2° (TELE) - 56.8° (WIDE) 　　　　　　　　 [4 : 3 mode] Horizontal : 24.0° (TELE) - 85.5° (WIDE) 　　　　　　　　　　　　 Vertical : 18.0° (TELE) - 63.3° (WIDE) WV-SFN611L [16 : 9 mode] Horizontal : 26.6° (TELE) - 95.1° (WIDE) 　　　　　　　　　　　　 Vertical : 14.9° (TELE) - 52.3° (WIDE) 　　　　　　　　 [4 : 3 mode] Horizontal : 26.7° (TELE) - 95.1° (WIDE) 　　　　　　　　　　　　 Vertical : 20.0° (TELE) - 70.2° (WIDE)
	Maximum Aperture Ratio	1 : 1.3 (WIDE) ~ 1 : 3.0 (TELE) *with Smart DOF (Depth of Field) mode
	Focusing Range	0.3 m ~ ∞
Adjusting Angle		Horizontal: ± 180°, Vertical: 0-85°,Image tilt adjustment range: -45°(Left) to +300°(Right)
Browser GUI	Cropping	H.264(1) / H.264(2) / H.264(3) / H.264(4) / H.264(all) / JPEG(1) / JPEG(2) / JPEG(3) Up to 4 image capture areas can be specified
	Camera Control	Brightness, AUX ON / OFF
	Display Mode	Spot, Quad : Image from 16 cameras can be displayed in 4 different Quad screens or 16 split screen (JPEG only). 20 characters camera title available.
	Digital Zoom	1x, 2x, 4x controlled by browser GUI
	Camera Title	Up to 20 alphanumeric characters
	Clock Display	Time : 12H/24H, Date : 5 formats on the browser, Summer time (Manual)
	Alarm Control	Reset
	One Shot Capture	A still picture will be displayed on a newly opened window.
	Audio	Mic (Line) Input : ON / OFF Volume adjustment : Low / Middle / High, Audio Output : ON / OFF Volume adjustment : Low / Middle / High
	SD Memory Data Download	Still or motion Images recorded in the SDXC/SDHC/SD memory card can be downloaded.
	GUI / Setup Menu Language	English, Italian, French, German, Spanish, Portuguese, Russian, Chinese, Japanese
	System Log	Up to 100 (Internal) Up to 4,000 (SDXC/SDHC/SD memory when the recording format is set to JPEG.) error logs
	Supported OS *3	Microsoft® Windows® 8, Microsoft® Windows® 7, Microsoft® Windows Vista®
	Supported Browser	Windows® Internet Explorer® 10.0 (32 bit), Windows® Internet Explorer® 9.0 (32 bit) Windows® Internet Explorer® 8.0 (32 bit), Windows® Internet Explorer® 7.0 (32 bit)
Network	Network IF	10Base-T / 100Base-TX, RJ-45 connector

|			
Network	Image Resolution	Image Capture Mode: 2 mega pixel [16:9] (30/60 fps)	WV-SFN631L : 1,920 x 1,080 / 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90
		Image Capture Mode: 2 mega pixel [4:3] (30fps)	WV-SFN631L : 1,600 x 1,200 / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120
		Image Capture Mode: 3 mega pixel [4:3] (30fps)	WV-SFN631L : 2,048 x 1,536* / 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120 *Used by super resolution techniques
		Image Capture Mode: 1.3 mega pixel [16:9] (30/60fps)	WV-SFN611L : 1,280 x 720 / 640 x 360 / 320 x 180 / 160 x 90
		Image Capture Mode: 1.3 mega pixel [4:3] (30fps)	WV-SFN611L : 1,280 x 960 / 800 x 600 / 640 x 480 / 400 x 300 / 320 x 240 / 160 x 120
	H.264 *4	Transmission Mode	Constant bitrate / Framerate priority / Best effort / Advanced VBR
		Frame Rate	1 / 3 / 5 / 7.5 / 10 / 12 / 15 / 20 / 30 / 60 fps
		Bit Rate/Client	64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 1,536 / 2,048 / 3,072 / 4,096 / 6,144 / 8,192 / 10,240 / 12,288 / 14,336 / 16,384 / 20,480 / 24,576 kbps
		Image Quality	LOW / NORMAL / FINE
		Refresh interval	0.2 / 0.25 / 0.33 / 0.5 / 1 / 2 / 3 / 4 / 5s
		Transmission Type	UNICAST / MULTICAST
	JPEG	Image Quality	10 steps
		Refresh interval	0.1 fps - 30 fps (JPEG frame rate will be restricted when displaying both JPEG and H.264 images.)
		Transmission Type	PULL / PUSH
	Audio Compression		G.726 (ADPCM) 32 kbps / 16 kbps, G.711 64 kbps / AAC-LC
	Audio Mode		OFF / Mic (Line) input / Audio output / Interactive (Half duplex) / Interactive (Full duplex)
	Authentication for Audio		Level 1 only / Level 2 higher / All users
	Total Bit Rate		64 / 128 / 256 / 384 / 512 / 768 / 1,024 / 2,048 / 4,096 / 8,192 kbps / Unlimited
	Supported Protocol		IPv6: TCP/IP, UDP/IP, HTTP, HTTPS, FTP, SMTP, DNS, NTP, SNMP, DHCPv6, RTP, MLD, ICMP, ARP IPv4: TCP/IP, UDP/IP, HTTP, HTTPS, RTSP, RTP, RTP/RTCP,FTP, SMTP, DHCP, DNS, DDNS, NTP, SNMP, UPnP, IGMP, ICMP, ARP

Network	FTP Client	Alarm image transmission, FTP periodic transmission (When the FTP transmission is failed, backup on an optional SDXC/SDHC/SD memory card is available.)
	No. of Simultaneous Users	Up to 14 users (Depends on network conditions)
	SDXC/SDHC/SD Memory Card (Option) * Manufactured by Panasonic (SD speed class 4 or higher) * Use the SD memory card that complies with UHS-1 (Ultra High Speed-1) in the case of SD Speed Class 10.	H.264 recording : Manual REC / Alarm REC (Pre/Post) / Schedule REC/ 　　　　　　　　 Backup upon network failure Compatible (JPEG only) JPEG recording : Manual REC / Alarm REC (Pre/Post) / 　　　　　　　　 Backup upon network failure Compatible 　　　　　　　　 SD (SDHC/SDXC) card : Panasonic 　　　　　　　　 2 GB, 4 GB*, 8 GB*, 16 GB*, 32 GB*, 64GB** model *SDHC card, ** SDXC card　(except miniSD card and microSD card)
	Employment of two SD cards	Dual Recording for Redundancy Series Recording for long time
	Cellular Phone Compatibility	JPEG image, AUX control (by access level)
	Mobile Terminal Compatibility	iPad, iPhone, iPod touch (iOS 4.2.1 or later), Android™ Terminal
Alarm	Alarm Source	3 terminals input, VMD, Command alarm, Audio detection alarm
	Alarm Actions	SDXC/SDHC/SD memory recording, E-mail notification, HTTP alarm notification Indication on browser, FTP image transfer, Panasonic protocol output
	Alarm Log	With SDXC/SDHC/SD memory card : Up to 50,000 logs for each SD memory card
	Schedule	Alarm / VMD / Access permission / H.264 recording / Scene file
Input/ Output	Monitor Output (for adjustment)	VBS : 1.0 V [p-p]/75 Ω, NTSC / PAL composite, ø3.5mm mini jack MONITOR OUT conversion plug included
	Microphone/Line Input	MIC IN and Line IN are selectable. ø3.5 mm monaural mini jack (monaural input) (Applicable microphone: Plug-in power type) Supply voltage: 2.5 V ±0.5 V Input impedance: Approx. 2 kΩ (unbalanced)
	Audio Output	ø3.5 mm stereo mini jack (monaural output) Output impedance: Approx. 600 Ω (unbalanced)
	External I/O Terminals	ALARM IN 1/DAY/NIGHT IN, ALARM IN 2/ALARM OUT, ALARM IN 3/AUX OUT
General	Safety	UL (UL60950-1), C-UL (CAN/CSA C22.2 No.60950-1), CE, IEC60950-1
	EMS	FCC (Part15 ClassA), ICES003 ClassA, EN55022 ClassB, EN55024
	Power Source and Power Consumption	When IR LED is ON WV-SFN631L DC power supply: 12 V DC/760 mA/Approx. 9.1 W PoE Device: 48 V DC/240 mA/Approx. 11.1 W (Class 0 device) WV-SFN611L DC power supply: 12 V DC/690 mA/Approx. 8.2 W PoE Device: 48 V DC/200 mA/Approx. 9.4 W (Class 0 device) * ONLY CONNECT 12 V DC CLASS 2 POWER SUPPLY.
	Ambient Operating Temperature	-10°C ~ +50°C (14 °F ~ 122 °F)
	Ambient Operating Humidity	20 ~ 90 % (no condensation)
	Dimensions	ø129.5 mm x 101 mm (H) {ø5-3/32 inches x 3-31/32 inches (H)} Dome radius 40 mm {1-9/16 inches}
	Mass (approx.)	Approx. 0.59kg {1.30 lbs}
	Finish	Main body: ABS resin, sail white / Dome section: Clear acrylic resin

*1 Converted value *2 Super Dynamic function is automatically set off on 60fps mode.
*3 Refer to "Notes on Windows Vista® / Windows® 7 / Windows® 8" on the provided CD-ROM for further information about system requirements for a PC and precautions when using Microsoft® Windows® 8 or Microsoft® Windows® 7 or Microsoft® Windows Vista®.
*4 Transmission for 4 streams can be individually set.

Part Names and Functions

MONITOR OUT terminal(factory shipment: NTSC monitor)
12 V DC power supply terminal
Screen display top (TOP)
Direction marker for installation (⇑TOP)
● Points up when installing to a wall.
Data Matrix: To our website*
NTSC/PAL switch
INITIAL SET button
ACT indicator
LINK indicator
SD MOUNT indicator
SD ERROR/AF indicator
WIDE button (moves the camera to the "Wide" side)
TELE button (moves the camera to the "Tele" side)
Auto focus (AF) button
Direction marker for installation (FRONT ⇓)
● FRONT must be positioned in front of the camera (on the Panasonic logo side)
SD slot 1 (SD1)　SD slot 2 (SD2)
SD ON/OFF button

(The illustrations are WV-SFN631L.)

* Depending on the scanning application used, the Data Matrix may not be able to be read correctly. In this case, access the site by directly entering the following URL.
http://security.panasonic.com/pss/security/support/qr_sp_select.html

Appearance

ø129.5(ø5-3/32")
101(3-31/32")
56(2-7/32")
SR40(1-9/16")

(The illustrations are WV-SFN631L.)

Unit: mm (inches)

DISTRIBUTED BY:

Panasonic

http://security.panasonic.com
http://www.facebook.com/PanasonicNetworkCamera

(2A-115AL)